



DCI – DIGITAL CONTROL INTERFACE MODULE

Interface to Silescent SimpleNet Digital Control

| | |
|-------------|------|
| Item Code | Type |
| Project | |
| Comments | Date |
| Prepared by | |

Silescent DCI (Digital Control Interface) modules provide an interface between 0-10VDC, 120VAC Phase, or Switched to Ground input control to the following Silescent SimpleNET Capable Lighting Fixtures: LP3/LS3/HS3/DD3/HD3.

SPECIFICATIONS & FEATURES

- Digital Control – via Silescent SimpleNET digital communication.
- Converts specified signal to Silescent SimpleNET Digital Control:
 - 0-10VDC control
 - 120VAC Phase control, or
 - Switched to Ground input
- Compact design allows for easy installation.

Warranty: 5 year limited warranty. Full warranty details available at www.silescent.com

MADE IN USA: All Silescent products are designed, engineered and manufactured In Ft. Lauderdale FL. Additionally, all Silescent products are ARRA & NAFTA compliant.



DCI3-010 Shown

ELECTRICAL DATA

- **Operating Temp:** -30°C to +50°C
- **Ambient Temp:** <35°C
- **Power Input:** 24VDC
- **Output:**
 - **DCI3-010** **Control Output:** 24VDC, 300mA
Control In (0-10): 10VDC, 2mA
 - **DCI3-120** 24VDC, 300mA
 - **DCI3-SG** 24VDC, 300mA
- **Rated Wattage:** 1.2 watts
- **Protection:** Internal Resettable fuse

ORDERING INFORMATION:

| Silescent Item Code | Description |
|---------------------|--|
| DCI3-010 | DCI, 0-10VDC input (Current Source Device), 10Vout |
| DCI3-120 | DCI, 120VAC Phase Control Input (preloaded) |
| DCI3-SG | DCI, Switched to Ground Input |



Information is subject to change without prior notification.